

# Supplement

Title:	374, 375, 376 Users	Supplement Issue:	<b>6</b>
Part Number:	3608883	Issue Date:	7/16
Print Date:	July 2010	Page Count:	5
Revision/Date:			

---

---

This supplement contains information necessary to ensure the accuracy of the above Users Manual.

## Change #1

On page 3, under **Warning** add the following:

- **When batteries are changed, ensure that the calibration seal in the battery compartment is not damaged. If damaged, the Meter may not be safe to use. Return the Meter to Fluke for replacement of the seal.**

## Change #2, 56750

On page 27, under Operating Altitude:

Change: Operating Altitude      3000 meters

To:                    Operating Altitude      2000 meters

## Change #3, 319




On page 4, add:

- **Measure a known voltage to verify product operation.**

- Do not use in CAT III or CAT IV environments without the protective cap of test probe. The protective cap decreases the expose probe metal < 4 mm. This decreases the possibility of arc flash from short circuits.

## Change #4, 63774, 319

On pages 7 and 8, update the **Symbols** table with the following and remove **TUV**:

	Conforms to relevant South Korean EMC Standards.
	Consult user documentation.
	Conforms to relevant Australian Safety and EMC standards.
<b>CAT II</b>	Measurement Category II is applicable to test and measuring circuits connected directly to utilization points (socket outlets and similar points) of the low-voltage MAINS installation.

<b>CAT III</b>	Measurement Category III is applicable to test and measuring circuits connected to the distribution part of the building's low-voltage MAINS installation.
<b>CAT IV</b>	Measurement Category IV is applicable to test and measuring circuits connected at the source of the building's low-voltage MAINS installation.

On page 27, replace the EMC with:

**Electromagnetic Compatibility (EMC)**

International..... IEC 61326-1: Basic Electromagnetic Environment

CISPR 11: Group 1, Class A

*Group 1: Equipment has intentionally generated and/or uses conductively-coupled radio frequency energy that is necessary for the internal function of the equipment itself.*

*Class A: Equipment is suitable for use in all establishments other than domestic and those directly connected to a low-voltage power supply network that supplies buildings used for domestic purposes. There may be potential difficulties in ensuring electromagnetic compatibility in other environments due to conducted and radiated disturbances.*

*Caution: This equipment is not intended for use in residential environments and may not provide adequate protection to radio reception in such environments.*

*Emissions that exceed the levels required by CISPR 11 can occur when the equipment is connected to a test object.*

Korea (KCC)..... Class A Equipment (Industrial Broadcasting & Communication Equipment)

*Class A: Equipment meets requirements for industrial electromagnetic wave equipment and the seller or user should take notice of it. This equipment is intended for use in business environments and not to be used in homes.*

USA (FCC) ..... 47 CFR 15 subpart B. This product is considered an exempt device per clause 15.103.

On page 28, replace the Safety Compliance section with:

Safety.....IEC 61010-1, pollution degree 2  
IEC 61010-2-032: CAT III 1000V / CAT IV 600V  
IEC 61010-2-033: CAT III 1000V / CAT IV 600V

Remove the Agency Approvals.