

Supplement

Title: 902 Users Supplement Issue: **3**
Part Number: 2547887, 2840080
Print Date: May 2006 Issue Date: 8/13
Revision/Date: 1, 3/07 Page Count: 4

This supplement contains information necessary to ensure the accuracy of the above Instruction Sheet.

Change #1

On page 23, under **Electrical Specifications**, replace the Temperature row with the following:

Temperature	-40 to 400 °C	0.1 °C	-40 to -10 °C $\pm 5.0\% + 1.5\text{ °C typical}$ -10 to 400 °C $\pm 1.0\% + 0.8\text{ °C typical}$
-------------	---------------	--------	--

Change #2

On page 3, under **Read First: Safety Information**, replace the 4th bullet with the following:

- Never use the Meter on a circuit with voltages higher than 600 V or a frequency higher than 60 Hz fundamental. The Meter may be damaged.**

On page 4, replace the third bullet with the following:

- To avoid false readings that can lead to electrical shock and injury, replace the batteries as soon as the low battery indicator (🔋) appears.**

On page 11, replace the first bullet with the following:

- If the resistance is $< 30 \Omega$, the continuity beeper will sound.

On page 20, under **Maintenance**, add the following note:

Note

When the Meter displays CAL, the unit will lock and no measurements can be made. The Meter must be sent to a Fluke Service Center for repair.

Change #3



On page 4, add:

- **Measure a known voltage to verify product operation.**

Change #4, 66422, 66561

On page 5, add the following to the **Symbols** Table:

CAT II	Measurement Category II is applicable to test and measuring circuits connected directly to utilization points (socket outlets and similar points) of the low-voltage MAINS installation.
--------	--

CAT III	Measurement Category III is applicable to test and measuring circuits connected to the distribution part of the building's low-voltage MAINS installation.
CAT IV	Measurement Category IV is applicable to test and measuring circuits connected at the source of the building's low-voltage MAINS installation.
	Conforms to CAN/CSA-C22.2 No. 61010-1, second edition, including Amendment 1.
	Conforms to relevant South Korean EMC Standards.

On page 24, remove **EMI, RFI, EMC** and replace **IP Rating** with:

IP Rating IEC 60529: IP40

On page 25, remove **Design Standards and Compliance, Agency Approvals** and **Over-voltage Category** and add:

Safety IEC 61010-1: 600 V CAT III, Pollution Degree 2

Electromagnetic Environment IEC 61326-1:
Portable

Electromagnetic Compatibility Applies to use in Korea only. Class A Equipment (Industrial Broadcasting & Communication Equipment) ^[1]

- [1] This product meets requirements for industrial (Class A) electromagnetic wave equipment and the seller or user should take notice of it. This equipment is intended for use in business environments and is not to be used in homes.